

Register 12—Fine Zero Adjust (address = 0x0C) (Read/Write)

BIT #	D7	D6	D5	D4	D3	D2	D1	D0
BIT Name	FZ7	FZ6	FZ5	FZ4	FZ3	FZ2	FZ1	FZ0

This register sets the code to the 8-bit fine DAC that adjust the magnitude of the zero output currents. Equations are given in Table 1. Negative numbers are in binary Two's Complement notation.

Bit Descriptions

FZ: Fine Zero Adjust (Bits 7-0)

These bits set the code of the fine DAC that adjusts the magnitude of the zero output currents.

	VOLTAGE REFERRED TO V _O PIN WITH RESPECT TO I _{RET}	CURRENT REFERRED TO I _{OUT} PIN
OVERALL	$V_{ZERO} = V_{Z\ PROGRAM} + V_{Z\ COARSE} + V_{Z\ FINE}$	$I_{ZERO} = I_{Z\ PROGRAM} + I_{Z\ COARSE} + I_{Z\ FINE}$
PROGRAM	$V_{Z\ PROGRAM} = \frac{3.5V_{REF}}{8}$	$I_{Z\ PROGRAM} = \frac{175V_{REF}}{8R_{VI}}$
COARSE DAC	$V_{Z\ COARSE} = \frac{V_{REF}}{80} \cdot \frac{N_{13}}{4}$	$I_{Z\ COARSE} = \frac{5V_{REF}}{8R_{VI}} \cdot \frac{N_{13}}{4}$
FINE DAC	$V_{Z\ FINE} = \frac{V_{REF}}{80} \cdot \frac{N_{12}}{64}$	$I_{Z\ FINE} = \frac{5V_{REF}}{8R_{VI}} \cdot \frac{N_{12}}{64}$
NOTE: N ₁₃ and N ₁₂ are assigned decimal values of registers 13 and 12, respectively.		

Table 1. Equations for Calculating Zero Output